

Celadon Inc.
RCV-5000 IR to RS-232 Output Table
Device: Marantz Plasma - PD5010D

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol
 Infrared Code Format: NEC - Device ID: 7B02
 Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description
 Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver
 RCV-5000 Data File: marantz1.hex
 Data: 9600 Baud, 8, O, 1, HEX Output
 Standard Transmit and Receive pinout

Marantz Command	Pronto Button	RCV-5000 Output
Video 1	0	DF 80 60 47 01 01 08
Video 2	1	DF 80 60 47 01 02 09
Video 3	2	DF 80 60 47 01 03 0A
HD	3	DF 80 60 47 01 05 0C
HD 2	4	DF 80 60 47 01 06 0D
RGB 1	5	DF 80 60 47 01 07 0E
RGB 2	6	DF 80 60 47 01 08 0F
RGB 3	7	DF 80 60 47 01 0C 13
Stadium	8	DF 80 60 51 01 02 13
Zoom	9	DF 80 60 51 01 03 14
Normal	10	DF 80 60 51 01 04 15
Full	11	DF 80 60 51 01 05 16
ON	12	9F 80 60 4E 00 CD
OFF	13	9F 80 60 4F 00 CE
TRUE	14	DF 80 60 51 01 06 17
Single Screen	15	DF 80 60 07 01 00 C7
Side by Side 1	16	DF 80 60 07 01 01 C8
Side by Side 2	17	DF 80 60 07 01 00 C9
PIP sub Sceen L	18	DF 80 60 07 01 00 CA
PIP sub Sceen R	19	DF 80 60 07 01 00 CB

Celadon, Inc.
 50 Mitchell Blvd.
 San Rafael, CA 94903
 Sales: (707) 648-1098
 Main Tel: (415) 472-1177
 Main Fax: (415) 472-1179
 sales@celadon.com